

LT-CKIT-40
Calibration KIT
2.92mm DC ~ 40 GHz
sales@lauftex.ru | lauftex.ru



1	Circuit breaker (m)	LT-CKIT-40-KM	1
2	Circuit breaker (f)	LT-CKIT-40-KF	1
3	Short circuit breaker (m)	LT-CKIT-40-DM	1
4	Short circuit breaker (f)	LT-CKIT-40-DF	1
5	Fixed load (m)	LT-CKIT-40-LM	1
6	Fixed load (f)	LT-CKIT-40-LF	1
7	Torque wrench		1
8	Adapter (2.92m-2.92m)	LT-CKIT-40-11	1
9	Adapter (2.92f-2.92f)	LT-CKIT-40-22	1
10	Adapter (2.92m-2.92f)	LT-CKIT-40-12	1
11	Storage box		1

Circuit breaker	Torque wrench
Phase deviation: $\leq \pm 6^\circ$	Opening size: 8mm, Torque: 0.9Nm
Circuit breaker	Adapter
Phase deviation: $\leq \pm 4.5^\circ$	VSWR: ≤ 1.12 (Return loss: $\geq 25\text{dB}$)
Fixed Load	Storage box
VSWR: ≤ 1.052 (Return loss: $\geq 32\text{dB}$)	275*200*80mm



Product	Material
Opener, Short Circuit Breaker, Load	Inner conductor: Beryllium copper Gold Plating Outer conductor: Beryllium copper Gold Plating
Torque wrench	Wrench head: tool steel Nickel plating Wrench handle: Aluminum anodized
Adapter	Inner conductor: Beryllium copper Gold Plating Outer conductor: Beryllium copper Gold Plating
Storage box	Wooden box

